


Sonneteer

Campion

ono

o

o i

**No test signal is better than her music
and no test instrument better than the
human ear.**

Campion should be placed in an open space away from moisture and with adequate ventilation.

The device is connected to the mains via an IEC mains lead. A plug is not supplied as standard. A plug appropriate for the country of purchase should be attached before use.

The IEC socket on the rear of the device has a replaceable fuse; see the specifications at the end of this manual for correct values.

For plug wiring details see specifications at the end of this manual.

Be sure that all appliances are turned off before disconnecting or connecting anything.

Campion has five inputs; Tp, CD, DIR, L1, L2 (Phono) and one output; LnOut. We recommend using DIR for best sonic performance. Tp, L1 should be used for line level signals e.g. Tape source. CD input is provided for high output level CD players. L2 is the phono input together with the earth stud, do not use this input for any other source.

Beware, do not have the Tape Source selected when LnOut is connected to it whilst recording as this will result in a very nasty experience.

For best loudspeaker connection use 4 mm banana plugs or spade connectors and be sure never to short positive and negative wires as this could have a detrimental effect on your speakers and your amplifier.

The controls on the front panel are, from left to right; Power, Source select and Volume.

When cleaning your Campion never use solvents. A clean dry cloth would be adequate.

Please note that there are no user serviceable parts inside the device and you should refer any problems to your dealer. Tampering with the device may void your warranty.

ni a p i i a i o n

Power	33Wrms 44Wrms	@8 Ohms @6 Ohms	
Input impedance	11k Ohms		
Gain	27dB		
Input sensitivity:			
	DIR	650 mVrms	
	CD	2 Vrms	
	L1,Tp	400 mVrms	
	L2 (Phono)	Gain = x1000 (47K @ 47pF)	
Bandwidth	8Hz to 80kHz		
THD	0.02% 0.035%	@1kHz @10kHz	@Full Power @Full Power
Size (mm)	434 x 74 x 280		
Fuse Values:			
UK/Europe/Australasia:	230V/240V; T 2.5 Amp		

Sonnenteer reserve the right to change specifications without prior notice.

Sonneteer

P.O. Box 163C, Esher, Surrey, KT10 0YH, England.
www.sonneteer.co.uk